



#### SIS LIVE Links

2 Whitehall Avenue, Kingston, Milton Keynes, MK10 0AX, UK  
tel: +44 (0)1908 865656

#### SIS LIVE OBs

Station Road, Langley, SL3 6DB, UK  
tel: +44 (0)1753 588088

#### SIS LIVE Europe

62 Boulevard Garibaldi, 75015 Paris, France  
tel: +33 960 123 356

#### SIS LIVE US

3312 Shorecrest Drive, Dallas, Texas 75235, USA  
tel: +1 214 350 1309

[sales@sislive.tv](mailto:sales@sislive.tv)

[www.sislive.tv](http://www.sislive.tv)



## RouteCase® Full HD Production Studio

RouteCase® is a powerful, highly portable and affordable production unit with 4 HD/SDI inputs plus a DVI-D input. Incorporating the latest in vision mixer technology with industry standard audio mixing facilities, RouteCase takes just a few minutes to set up, and offers true 'plug and play' operation.

Housed in a compact and rugged custom built flight case, RouteCase can handle asynchronous sources in many formats with comprehensive picture monitoring via the built in 15" HD LCD monitor.

RouteCase is ideally suited for live operations such as satellite newsgathering, outside broadcasts, sporting events and live streaming content creation.

[www.sislive.tv](http://www.sislive.tv)



## FEATURES

- Compact and rugged field production unit
- Powerful vision mixer with 4 HD/SD SDI inputs and 1 DVI-D input.
- 1080i, 1080 PsF, 720p HD, 480/576 SD modes
- SDI 480 /576 formats accepted in HD mode via 2 inbuilt upconverters (I/Ps 3 /4)
- Fully synchronous mixing between all inputs
- Automatic embedded audio switching
- Tally output for external cues
- 10 channel audio mixer
- 15" HD LCD multi-viewer screen
- 12 volt operation
- Optional multi-channel embedder/de-embedder

## TECHNICAL SPECIFICATION

### VIDEO

Digital vision mixer supporting a number of HD and SD formats

1080/59.94i 1080/50i

720/59.94p 720/50p

1080/24PsF 1080/23.98PsF

480/59.94 576/50i

2 built in upconverters (I/P 3 - I/P 4)

4 video inputs

DVI-D input

Fully synchronous mixing between inputs

2 main outputs

Switchable aux output

Internal test pattern generator

Selectable wipe patterns

### AUDIO

10 channel stereo audio mixer

2 mic channels with gain and EQ

### MONITOR

Multi-viewer output on built in 15" HD LCD monitor

### POWER

12v input 40w power consumption

4½ hours operation using 2 x 90Wh camera batteries via optional battery adaptor

### ACCESSORIES

Mains 12v Power supply

Battery power adaptor to fit 2 V-lock or AB Gold mount batteries

### OTHER

Weight: 4.8kg

Dimensions:

Length 410mm

Depth 300mm

Height 100mm